

➤ S212系列滤波器



CE

特征

- ◆ 双极共模滤波
- ◆ 非常高的共模和差模抑制比
- ◆ 适用于共模干扰非常强烈的现场

典型应用

- ◆ 铁路设备
- ◆ 超声和激光类设备

技术参数

额定电压	250VAC
工作频率	50/60Hz
线-线耐压	1500VDC
线-地耐压	2000VAC
绝缘电阻	>100MΩ @500VDC
工作温升	<30°C@40°C
气候类别 (IEC 60068-1)	25/085/21


选型列表

产品型号	额定电流 (A)	泄漏电流 (mA) @250VAC	外壳	连接端子		电路原理图
				通用	可选	
DTS212-1-W20-B15	1	<0.5	B15		—	
DTS212-3-W20-B15	3	<0.5	B15		—	
DTS212-6-F8-D15	6	<0.5	D15			
DTS212-10-F8-D15	10	<0.5	D15		—	
DTS212-20-M6-D35	20	<0.5	D35			
DTS212-30-M6-D45	30	<0.5	D45		—	
DTS212-50-M6-D55	50	<0.5	D55		—	


S212系列滤波器

插入损耗


—— 共模 - - - - - 差模 (50 Ω / 50 Ω 测量系统 符合 IEC / CISPR NO. 17)




DTS212-1-W20-B15




DTS212-3-W20-B15




DTS212-6-F8-D15




DTS212-10-F8-D15



DTS212-20-M6-D35




DTS212-30-M6-D45




DTS212-50-M6-D55


外形尺寸(mm)




B15 (W20)




D15 (F8)




D35 (M6)



D35 (F8)



D45 (M6)



D55 (M6)